zurück zur
Übersicht

back to overview




# Service Manual

Version 1.0 - englisch

## Audio 10 ECE Typ 3100




- *Circuit diagram*
- *Components schematics*
- *Test program / Reset*
- *Anti-theft Divice*
- *Technical Data*
- *Spare Parts List*

BECKER GMBH
Im Stöckmädle 1
76307 Karlsbad, Germany
Telefon +49(0) 7248 710


Part. No.







## RESET-release MB-MY99

 and B and C press simultanously .

Action: Sound source will be interrupted for app. 1 second and display set up again.

## Test programe MB-MY99

| | | | |
|---|---|---|---|
| 1 and 2 after | press simultanously | BECKER | Becker-Test mode is activated |
| 3 | press once | SIG<br>10 89.5 | f. e. 10 = Field strength<br>f. e. 89.5 = Frequency (MHz) |
| 3 | press twice | TPV 2 | Increase TA<br>Settings: 0-1-2-3<br>select with △ , ▽ |
| 3 | press 3 times | ECE<br>100 9 | 100 = Grid FM<br>9 = Grid AM |
| 3 | press 4 times | TYP 3100 | |
| 3 | press 5 times | SEA<br>W1001052 | |
| 3 | press 6 times | SW<br>03/00 | Display:<br>actual software version |
| 3 | press 7 times | END | after 5 seconds test programme will be quit automaticly |




## Entering the code number




Set each digit of the code with the (B) or (C) button and confirm individually with the (A) button. The dash prompting the entry of the next digit flashes. The digits can be reselected for correction via the (A) button.




## Technical Data


| | |
|---|---|
| **Wave band:** | FM 87,5 MHz - 108 MHz<br>AM 531 kHz - 1620 kHz<br>LW 153 kHz - 282 kHz<br>SW 5800 kHz - 6250 kHz |
| **Station memory:** | 4 stations can be stored for each of the wave bands FM1 and FM2, AW, LW and SW |
| **Frequency range:** | 50 Hz - 16 kHz Cassette<br>30 Hz - 15 kHz FM<br>50 Hz - 2,5 kHz AM, LW, SW |
| **EON-Function:** | |
| **Regional mode:** | switching on / switching off |
| **Regional mode:** | FM, AW, LW |
| **Output power:** | 4 x 20 Watt at 4 Ohm (10%Klirr) |
| **Line cross section:** | min. 0,75 mm² |
| **Speaker Impedance:** | min. 4 Ohm |
| **GAL:** | fixed defined volume increase |
| **Antenna:** | Impedanz 50 Ohm |
| **Telephone mute:** | Low active level < 2 Volt |
| **Supply voltage:** | 12 Volt |
| **Tape deck:** | Autoreverse, electronical control (Full Logic Control)<br>Titel search forward/rewind |
| **Soundsystem:** | Connection only via D2B optical interface |
| **CD connection:** | Only MB-CD changers with D2B optical interface can be connected. |
| **Playable CD's:** | Only CDs which conform to DIN EN 60908 may be used.<br>The use of 8 cm CDs with adapter is not recommended. |



BECKER
AUTOMOTIVE SYSTEMS



BECKER
AUTOMOTIVE SYSTEMS

SPG
ST1
ST2
ST3
NF
DIG
Connector
3 Connector block (Board 4040)
4 Interface (Board 4010)
Power supply
5
Interface
Illumination;
Tel.-Mute;
GAL; 12Vout;
CAN,-K-Bus
10
AF-section
Audio-controller;
AF-amplifier
8
Tuner AM/FM
6
Control
Tape deck,
Dolby B
12
Interface
d2b-optical;
AD / DA-converter
9
Tuner RDS-Decoder
7
Steuerung
Prozessor,
Shiftregister,
11
Front
13 Front Interface (Board 4010)
14 Frontprocessor, Keyboard (Board 9090)
15 Display (Board 9090)




| PIN | Chamber A | Chamber B | Chamber C |
|---|---|---|---|
| 1 | Speed dependent Vol. control | Loudspeaker rear right + | not assigned |
| 2 | K-line | Loudspeaker rear right - | not assigned |
| 3 | Telephone mute | Loudspeaker front right + | |
| 4 | Terminal 30, Battery | Loudspeaker front right - | Wake up line |
| 5 | Control output 12V | Loudspeaker front left + | Battery 12V Fuse |
| 6 | Battery 12V Fuse | Loudspeaker front left - | Terminal 31, Ground |
| 7 | Terminal 15, Ignition | Loudspeaker rear left + | |
| 8 | Terminal 31, Ground | Loudspeaker rear left - | |



to connector block (Board 4040)
BU1
CON3300
NFHRP
NFHRM
NFFRP
NFFRM
NFFLP
NFFLM
NFHLP
NFHLM
UD5V
GNDS1
GAL
TELMU
ANTOU
CANHI
CANLO
WAKUP
KLEIT
KL58
KL151
KL152
GNDS2
GNDS3
GNDS4
NC
KL30S1
KL30S2
KL30S3
SPG
ST3
NF
C50
KL30B
100U
C51
10N
R50
R51
R52
15R
NFHR+
NFHR-
NFFR+
NFFR-
NFFL+
NFFL-
NFHL+
NFHL-
KL30S
KL75
D50 BLM21A601S
D51
BLM21A601S
KBUS
WAKUP
CANL
CANH
AUTAN
TELMU
GAL
RAMSH
D52
KL58D
BLM21A601S
C77 C76 C75 C74 C73 C72 C71 C70 C65
100N
10N
C64 C63 C62
C59 C58 C57
C56
C54
100N
S3B
C55
DI50
D53
200U
UBATT
C53
2M2
C52
100N


BECKER
AUTOMOTIVE SYSTEMS

ST3
SPG
ST2
ST1
KL30S
Voltage control
R602
22K
T606
BC856B
R618
10K
R603
4K7
C603
47N
R619
10K
T607
BC846B
R620
10K
R621
10K
ONUG
SPUSW
UBATT
C606
100N
UG9V
IC601
IN
INHIBIT
OUT
GND
R
TLE4276GV
R605
39K
56U
C607
R604
15K
UD5V
C609
100N
56U
C610
R623
0R
SI
IN
NC5
GND8
GND7
GND6
GND5
NC4
OUT
SO
IC602
TLE4269
RE
D
NC1
GND1
GND2
GND3
GND4
NC2
NC3
R
R615
1K
R614
1K
RAMSH
C613
100N
UD5V
2SD2394F
T601
R608
270R
C612
22U
DI603
6V8 5%
R609
100R
C611
100P
T602
BC858C
UG5V
UG5V
RESEQ
NF
DIG




Oscil.

Synthesizer


FM-Quality


AM-nois reduction

AM-Signal way

FM-Signal way


BECKER
AUTOMOTIVE SYSTEMS



SPG
ST1
ST2
ST3
NF
RDSC1
RDSD1
MPX1
UG5V
RDS-
Decoder
QUAL
RDDA
VREF
MPX
VCCA
GNDA
CIN
SCOUT
RDCL
T57
OSCIO
OSCI
VCCD
GNDD
TEN
TCTR
IC1401
SAA6579T
C1401
4U7
C1402
330P
R1401
10R
C1407
10U
C1403
100N
C1404
560P
R1402
820R
Q1401
4M332Hz
C1405
47P
C1406
82P


Circuit additional
Synthesizer-PLL
SPG
ST1
ST2
ST3
NF
R1160
820K
T1151
2SC2814
R1161
1K
OSC2I
OSC2O




Audio controller

SPG
UG9V
UG5V
R2001
22K
ST1
DATA2
CLOK2
ST2
DIG
ST3
SMUTQ
NF
NFPIP
R2002
47K
C2006
22N
NFAM
R2003
2K2
C2007
100N
C2003
33N
R2008
8K2
C2010
4U7
NFCCR
R2004
3K9
NFDACR
C2001
1U
R2009
0R
NFTUR
R2005
3K9
C2008
220N
C2004
3N9
R2010
8K2
C2011
4U7
NFCCL
R2006
3K9
NFDACL
C2002
1U
R2011
0R
NFTUL
R2007
3K9
C2009
220N
C2005
3N9
C2012
2N7
C2013
4U7
C2014
47N
C2015
47N
C2016
10U
C2017
4U7
1 TRR
2 INR
3 OUTR
4 LOUDR
5 INR3
6 INR2
7 INR1
8 MONO
9 LOUDL
10 CDGND
11 INL3
12 INL2
13 INL1
14 CSM
15 INL
16 OUTL
IC2001
TDA7342
32 TRL
31 GND
30 VCC
29 CREF
28 SCL
27 SDA
26 DGND
25 OUTLF
24 OUTRF
23 OUTLR
22 OUTRR
21 SM
20 BOUTR
19 BINR
18 BOUTL
17 BINL
C2018
2N7
C2019 47P
C2020 1U
C2025
100N
NFFRL
NFFRR
NFHEL
NFHER
C2021
220N
C2022
150N
C2023
220N
C2024
150N
R2012
5K6
R2013
5K6



Fot-Unit

d2b-optical „CONAN“

A/D-D/A-converter




SPG
ST1
ST2
ST3
DIG
NF

## Illumination

BELIN
BELON
KL58D
T861 KRC103S
R864 100K
R863 3K3
R865 47K
C863 1U
C862 4U7
R862 12K
DI861 BAW56
R861 1K
C861 1U

## Wake up-line

UBATT
UD5V
WKUPI
UG5V
WKUPO
T853 KRC103S
T852 KRA103S
BAS216 DI853
R851 1K
C852 10N
R850 15K
WAKUP
T855 KRA103S
R852 2K2
T854 BC817/40
R853 680R
R854 22R
R857 22R
DI854 BAS216
R855 10K

## K-line

KBRXD
KBTXD
T840 KRA103S
T841 KRC103S
T842 BC848B
R841 47K
R843 56K
DI840 5V6 2%
R842 470K
R844 100R
KBUS
T843 KRC103S

## CAN-Physicallayer

CANIHQ
CANTX
CANRX
CAERQ
CASTQ
CAENB
T870 KRC103S
IC870 TJA1053
INH, TX, RX, ERR, STB, EN, WKUP
BAT, GND, CANL, CANH, VCC, RTL, RTH
RECEIVE LOGIC AND ERROR DETECTION
BUS DRIVER AND PROTECTION
RECEIVE AND STAND-BY LOGIC
C870 100N
D870 BLM11A221S
D871 BLM11A221S
D873 B82790
CANL
CANH
R872 1K6
R873 1K6
C871 100N
UBATT
UG5V

## Control „ON“

UD5V
CANIHQ
KL75Q
FPANQ
WKUPI
PWUPQ
BELON
CCINS
R830 22K, R831 47K, R832 47K, R833 22K
C830 100N, C831 100N
DI830 BAW56, DI831 BAW56
C832 100N, C833 100N
R834 22K, R835 47K, R836 47K, R837 22K
C834 100N, DI832 BAW56, C840 100N
R838 22K, R839 47K, R859 47K, R860 22K

## EEPROM

IC830 24LC04B
GND, A2, A1, A0, SDA, SCL, WP, VCC
DATA2
CLOK2
R845 220R
UG5V
C835 47N
R898 10K
FM1EMP
FM1EM
C898 1U

## 12V out

AUTAN
ONANT
IC881 BSP452
OUT, GND, IN, VCC
R881 10K
R882 10K
R883 10K
C881 100N
UBATT
C882 100N

## Tel.-Mute-input

UG5V
TELMU
TELUP
R885 10K
R887 22K
T885 BC858C
DI885 BAS216
R886 22K
R888 10K

## GAL-input

UG5V
GAL
GALUP
R890 10K
R892 22K
T890 BC858C
DI890 BAS216
R891 22K
R893 1K

## Inverter -ignation KL75

UD5V
KL75
KL75Q
DI834 BAS216
C837 100N
IC831 TC7S14F
R846 22K
R847 10K
DI833 BAS216
C836 10N
R848 68K




Processor

EPROM

Latch1 Output

Latch2 Input

Adress-Latch

RAM

Shiftregister

Selektion
Latch1: Output
Latch2: Input

Tape monitoring
IC702
74HC03
74HC03 PWR IC702
14 VCC
7 GND
C724
100N
R725 33K
R726 33K
R727 47K
KRA105S
T702
to Tape deck
ST701
LED
CCPSE
REEL_F
CCMOD
REEL_R
CCLDG
CCEJT
CCMOT
PGND
UBATT
CCINS
CCMET
PBREF
TRK2L
TRK2R
TRK1R
TRK1L
DIG
ST3
ST1
ST2
SPG
NF
CCRUN
CCTR2
UG5V
CCMOQ
UG9V
NFCCL
CCMSB
CCDOC
CCDOB
NFCCR
R736 47K
R735 47K
R729 22K
R730 22K
R728 10R
C725 100U
MP701
MP703
MP702
R732 0R
CC-amplifiere, Dolby B
IC701
CXA2510Q
L= nodolby
TRK_1
120 us
nomute
G1FB
MSTC
DGND
MSOUT
NC2
NRSW
INSW
TAPESW
DRSW
MSMODE
PBFB1
PBRIN1
PBREF1
PBFIN1
PBGND
VCT
PBFIN2
PBREF2
PBRIN2
PBFB2
P701 10K
P702 10K
R703 180K
R701 11K
R702 16K
C705 15N
R704 100R
R714 100R
R712 16K
R711 11K
R713 180K
C715 15N
C720 22U
C706 330P
C707 330P
C716 330P
C717 330P
C722 4N7
C721 470N
R722 68K
R721 3K9
C702 100N
C704 4U7
C723 100N
R723 470K
C712 100N
R720 18K
C714 4U7

ST3 ST2 ST1 SPG NF DIG

ST3 ST2 ST1 SPG

FPDAT FPCLK FPANQ LCDAT LCCLK KONUM RESEQ TALED UD5V UG5V UG9V LEDON BPWM2 KL30B

C806 C807 C808 C811 C812 C813 C814 C815 C816 C817 C818 C819 C820

100P 100P 100P 100P 100P 100P 100P 100P 100P 100P 100P 100P 100P

ST801

| Signal | Pin |
|---|---|
| FPDAT | 16 |
| FPCLK | 15 |
| FPANQ | 14 |
| | 13 |
| | 12 |
| LCDAT | 11 |
| LCCLK | 10 |
| KONUM | 9 |
| RESEQ | 8 |
| TALED | 7 |
| UD5V | 6 |
| UG5V | 5 |
| UG9V | 4 |
| BELCD | 3 |
| BELTA | 2 |
| | 1 |

to Front (Board 9090)

T808 KRA102S

T805 KRA103S

T807 BCX52/16

T806 KRC102S

R811 1K

R810 1K

R809 10K

C805 1N

C821 100U

R820 10R

R821 10R

R822 10R

Illumination control
Keyboard and Display




to Mainboard 4010

BU1801 FRONT3310

1 GNDUP
2 BELTA
3 BELCD
4 UG9V UG5V
5 UD5V
6 TALED
7 RESEQ
8 KONUM
9 LCCLK
10 LCDAT
11 LCDA0
12 LCDCS
13 FPANQ
14 FPCLK
15 FPDAT
16

Illumination on / off-switch

R1801 680R LD1801 LYT670 LD1802 LYT670

Keyboard left

R1809 560R R1810 560R LD1831 LYT670 LD1832 LYT670 LD1833 LYT670 LD1834 LYT670 LD1835 LYT670 LD1836 LYT670 R1816 820R R1817 820R

Keyboard right

R1811 560R R1812 560R LD1837 LYT670 LD1838 LYT670 LD1839 LYT670 LD1840 LYT670 LD1841 LYT670 LD1842 LYT670 R1818 820R R1819 820R

Keyboard left

R1813 820R LD1843 LYT670 LD1844 LYT670

CC-slot

R1814 470R LD1846 LYT670 LD1847 LYT670 LD1848 LYT670

Keyboard right

R1815 680R LD1849 LYT670 LD1850 LYT670 LD1851 LYT670

Display

R1802 1K5 R1803 1K5 R1804 1K5 R1805 1K5 LD1803 LYT670 LD1804 LYT670 LD1805 LYT670 LD1806 LYT670 LD1807 LYT670 LD1808 LYT670 LD1809 LYT670 LD1810 LYT670 LD1811 LYT670 LD1812 LYT670 LD1813 LYT670 LD1814 LYT670

R1841 470R R1842 4K7 BC818/16 T1802

C1803 22P Q1801 4M19 C1802 22P C1836 4N7

Reset-control

KRC104S DI1803 BAS216 R1849 22K T1805

R1836 100K R1844 100K R1837 1M R1848 22K

D1801 BLM11A221S

IC1802 PD754302

| Pin | Name | Name | Pin |
|---|---|---|---|
| 1 | GND | P50 | 36 |
| 2 | X1 | P51 | 35 |
| 3 | X2 | P52 | 34 |
| 4 | RESET | P53 | 33 |
| 5 | P33/MD3 | P60/KR0 | 32 |
| 6 | P32/MD2 | P61/KR1 | 31 |
| 7 | P31/MD1 | P62/KR2 | 30 |
| 8 | P30/MD0 | P63/KR3 | 29 |
| 9 | P81 | P70/KR4 | 28 |
| 10 | P80 | P71/KR5 | 27 |
| 11 | P23 | P72/KR6 | 26 |
| 12 | P22/PCL | P73/KR7 | 25 |
| 13 | P21/PTO0 | P13/TI0/TI1 | 24 |
| 14 | P20/PTO0 | P12/INT2 | 23 |
| 15 | P03/SI | P11/INT1 | 22 |
| 16 | P02/SB0/SO | P10/INT0 | 21 |
| 17 | P01/SCK | VCC | 20 |
| 18 | P00/INT4 | IC | 19 |

Front-Processor

R1831 1K C1811 100P C1810 4N7 C1801 100N

Keyboard left

S1801 1 2 HUP; S1801 3 4 SCAN; S1801 5 6 AUP; S1801 7 8 TA; S1801 9 10 HDN; S1801 11 12 TON; S1801 13 14 ADN; S1801 15 16 EJT

Keyboard right

S1802 1 2 1; S1802 3 4 FM; S1802 5 6 3; S1802 7 8 AM; S1802 9 10 4; S1802 11 12 CD; S1802 13 14 2; S1802 15 16 CC; S1802 17 18 RDS

DI1801 BAS216

Increment pick-up Volume, On / off-switch

C1805 1N R1833 22K S1831 VOL B A C R1832 22K C1804 1N S1831 EIN/AUS 5 4

Anti-Theft-Diode control

DI1804 BAS216 R1854 470R R1852 120R R1851 180R LD1861 LST670 T1806 C1809 1U KRC102S

Wake up Front-Processor

R1846 100K R1847 100K T1801 BC848B




S[0..43]

DP1801

HEATSEAL3100

IC1801

PCF8576T

LCD-Driver

Contrast control

R1865 47K

T1803

KRC103S

KONUM

R1862 6K8

R1864 5K1

R1861 180K

C1861 47N

GNDUP

BAS216 DI1805

UG9V


LCCLK

LCDAT




## 4010 Main Board






## 9090 Front







BECKER
AUTOMOTIVE SYSTEMS




Components side - Board 9090




Soldering side - Board 9090

| Pos. | Part.-No. | Denomination |
|---|---|---|
| 1 | 1284614 | CHASSIS |
| 2 | 1309765 | COVER, CHASSIS |
| 3 | 1284622 | HOLDING SPRING-RIGHT |
| 4 | 1284630 | HOLDING SPRING-LEFT |
| 5 | 1246909 | HEAT SINK 3310 WGR11318 |
| 6 | 1271997 | COVER -D2B HEADER- AMP 969 272-2 |
| 7 | 1246917 | IC-HOLDER |
| 8 | 1248316 | SCREENING FRAME-FM- WITH ANT.SOCKET |
| 9 | 1278916 | CONNECTOR 21 POL D&R K37000300 |
| 10 | 1271210 | TAPEDECK ASSY ALP GR71S31B GR-S |
| 11 | | OPERATION ESCUTCHEON (NOT AVAILABLE CPL) |
| 12 | 1313266 | OPERATION ESCUTCHEON WITH CLOSING FLAP |
| 13 | 1342282 | P.C. BOARD 9090 FRONT/LCD |
| 14 | 1342312 | KEY EJECT |
| 15 | 1342320 | KEY SC |
| 16 | 1342339 | KEY MUTE |
| 17 | 1342355 | KEY TONE |
| 18 | 1342363 | KEY CC |
| 19 | 1342371 | KEY FM |
| 20 | 1342381 | KEY AM |
| 21 | 1342398 | KEY CD |
| 22 | 1342401 | KEY CROSS TRANSMITTER SEARCH |
| 23 | 1342411 | KEY CROSS STATION BUTTONS |
| 24 | 1342428 | KEY RDS |
| 25 | 1313428 | CONTACT MAT, LEFT 3100 |
| 26 | 1313436 | CONTACT MAT, RIGHT 3100 |
| 27 | 1313369 | TORSIO SPRING |
| 28 | 1313355 | CLOSING FLAP |
| 29 | 1313339 | LEVER CONTROL |
| 30 | 1313347 | CONTROL CLOSING FLAP |
| 31 | 1284177 | BUTTON |
| 32 | 1313411 | LIGHT CONDUCTOR (CC) 3100 |
| C101 | 1237683 | CECA-CH 4P7 J NP0 0603 BAW SPE0030A315 |
| C103 | 1237683 | CECA-CH 4P7 J NP0 0603 BAW SPE0030A315 |
| C104 | 1223968 | CECA-CH 33P J NP0 0603 BAW SPE0030A315 |
| C105 | 1223976 | CECA-CH 47P J NP0 0603 BAW SPE0030A315 |
| C107 | 1243012 | CECA-CH 27P J NPO 0603 BAW SPE0030A315 |
| C108 | 1223941 | CECA-CH 18P J NP0 0603 BAW SPE0030A315 |
| C109 | 1119060 | CECA-CH 1N K X7R 0805 BAW SPE0015A315 |
| C110 | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| C111 | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| C114 | 1283499 | CECA-CH 1U K X7R 0805 10V MUR GRM 40 |
| C115 | 1246321 | CECA-CH 220N K X7R 1206 BAW SPE0036A315 |
| C116 | 1182943 | CECA-CH 47N K X7R 0805 BAW SPE0015A315 |
| C117 | 1119222 | CECA-CH 470P K X7R 0805 BAW SPE0015A315 |
| C118 | 1306170 | AL-ELCA 100U M 1000/85G NCC SRM-VB RM2,5 |

| | | |
|---|---|---|
| **C119** | 1119060 | CECA-CH 1N K X7R 0805 BAW SPE0015A315 |
| **C121** | 1119060 | CECA-CH 1N K X7R 0805 BAW SPE0015A315 |
| **C122** | 1119060 | CECA-CH 1N K X7R 0805 BAW SPE0015A315 |
| **C123** | 1119060 | CECA-CH 1N K X7R 0805 BAW SPE0015A315 |
| **C131** | 1238787 | CECA-CH 5P6 J NP0 0603 BAW SPE0030A315 |
| **C132** | 1119060 | CECA-CH 1N K X7R 0805 BAW SPE0015A315 |
| **C133** | 1119060 | CECA-CH 1N K X7R 0805 BAW SPE0015A315 |
| **C134** | 1226991 | CECA-CH 2P2 J NP0 0603 BAW SPE0030A315 |
| **C1401** | 1283235 | CECA-CH 4U7 K X5R 1206 10V MUR GMR42-6 |
| **C1402** | 1275992 | CECA-CH 330P J NP0 0603 BAW SPE0030A315 |
| **C1403** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C1404** | 1156561 | CECA-CH 560P J NP0 0805 BAW SPE0003A315 |
| **C1405** | 1223976 | CECA-CH 47P J NP0 0603 BAW SPE0030A315 |
| **C1406** | 1234463 | CECA-CH 82P J NP0 0603 BAW SPE0030A315 |
| **C1407** | 1243934 | AL-ELCA 10U M 16V G BAW SPE0069A31 RM2,5 |
| **C1500** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C1501** | 1223951 | CECA-CH 22P J NP0 0603 BAW SPE0030A315 |
| **C1502** | 1223951 | CECA-CH 22P J NP0 0603 BAW SPE0030A315 |
| **C1503** | 1283499 | CECA-CH 1U K X7R 0805 10V MUR GRM 40 |
| **C1504** | 1283499 | CECA-CH 1U K X7R 0805 10V MUR GRM 40 |
| **C1505** | 1283499 | CECA-CH 1U K X7R 0805 10V MUR GRM 40 |
| **C1506** | 1243012 | CECA-CH 27P J NPO 0603 BAW SPE0030A315 |
| **C1507** | 1223951 | CECA-CH 22P J NP0 0603 BAW SPE0030A315 |
| **C1508** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C1509** | 1233971 | CECA-CH 10P J NP0 0603 BAW SPE0030A315 |
| **C151** | 1257821 | CECA-CH 6N8 K B 0805 50V PDAG MUR GRM425 |
| **C1510** | 1233971 | CECA-CH 10P J NP0 0603 BAW SPE0030A315 |
| **C1511** | 1233971 | CECA-CH 10P J NP0 0603 BAW SPE0030A315 |
| **C1512** | 1173324 | CECA-CH 1N J NP0 0805 BAW SPE0003A315 |
| **C1513** | 1233971 | CECA-CH 10P J NP0 0603 BAW SPE0030A315 |
| **C1514** | 1233971 | CECA-CH 10P J NP0 0603 BAW SPE0030A315 |
| **C1515** | 1233971 | CECA-CH 10P J NP0 0603 BAW SPE0030A315 |
| **C1516** | 1083899 | CECA-CH 820P J NP0 1206 BAW SPE0006A315 |
| **C1517** | 1083899 | CECA-CH 820P J NP0 1206 BAW SPE0006A315 |
| **C1518** | 1275879 | ALCA-CH 10U M 16V I G BAW SPE0162A312 |
| **C1519** | 1275879 | ALCA-CH 10U M 16V I G BAW SPE0162A312 |
| **C152** | 1223992 | CECA-CH 150P J NP0 0603 BAW SPE0030A315 |
| **C1520** | 1283499 | CECA-CH 1U K X7R 0805 10V MUR GRM 40 |
| **C1521** | 1283499 | CECA-CH 1U K X7R 0805 10V MUR GRM 40 |
| **C1522** | 1275879 | ALCA-CH 10U M 16V I G BAW SPE0162A312 |
| **C1523** | 1275879 | ALCA-CH 10U M 16V I G BAW SPE0162A312 |
| **C1524** | 1253441 | FOCA-CH 10N J 1206 50V G PAN ECHU |
| **C1525** | 1253441 | FOCA-CH 10N J 1206 50V G PAN ECHU |
| **C1526** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C1527** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C1528** | 1223968 | CECA-CH 33P J NP0 0603 BAW SPE0030A315 |
| **C153** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |

| | | |
|---|---|---|
| **C1530** | 1119117 | CECA-CH 10N J X7R 0805 BAW SPE0014A315 |
| **C1550** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C1551** | 1119117 | CECA-CH 10N J X7R 0805 BAW SPE0014A315 |
| **C1552** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C1553** | 1275879 | ALCA-CH 10U M 16V I G BAW SPE0162A312 |
| **C1554** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C1555** | 1275879 | ALCA-CH 10U M 16V I G BAW SPE0162A312 |
| **C1556** | 1119117 | CECA-CH 10N J X7R 0805 BAW SPE0014A315 |
| **C1557** | 1283499 | CECA-CH 1U K X7R 0805 10V MUR GRM 40 |
| **C156** | 1234536 | CECA-CH 100P J NP0 0603 BAW SPE0030A315 |
| **C157** | 1119176 | CECA-CH 22N J X7R 0805 BAW SPE0014A315 |
| **C159** | 1119222 | CECA-CH 470P K X7R 0805 BAW SPE0015A315 |
| **C160** | 1252690 | CECA-CH 470P J NP0 0603 BAW SPE0030A315 |
| **C161** | 1223933 | CECA-CH 15P J NP0 0603 BAW SPE0030A315 |
| **C162** | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| **C163** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C164** | 1172050 | AL-ELCA 47U M 16V G BAW SPE0060A31 RM2,5 |
| **C165** | 1243934 | AL-ELCA 10U M 16V G BAW SPE0069A31 RM2,5 |
| **C166** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C168** | 1119060 | CECA-CH 1N K X7R 0805 BAW SPE0015A315 |
| **C169** | 1119060 | CECA-CH 1N K X7R 0805 BAW SPE0015A315 |
| **C170** | 1182943 | CECA-CH 47N K X7R 0805 BAW SPE0015A315 |
| **C1801** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C1802** | 1223951 | CECA-CH 22P J NP0 0603 BAW SPE0030A315 |
| **C1803** | 1223951 | CECA-CH 22P J NP0 0603 BAW SPE0030A315 |
| **C1804** | 1173324 | CECA-CH 1N J NP0 0805 BAW SPE0003A315 |
| **C1805** | 1173324 | CECA-CH 1N J NP0 0805 BAW SPE0003A315 |
| **C1809** | 1238647 | TAKO-CH 1U K B G 35V BAW SPE0005A313 |
| **C1810** | 1166751 | CECA-CH 4N7 K X7R 0805 BAW SPE0015A315 |
| **C1811** | 1234536 | CECA-CH 100P J NP0 0603 BAW SPE0030A315 |
| **C1836** | 1166751 | CECA-CH 4N7 K X7R 0805 BAW SPE0015A315 |
| **C1861** | 1182943 | CECA-CH 47N K X7R 0805 BAW SPE0015A315 |
| **C2001** | 1258907 | ALCA-CH 1U M 50V I G BAW SPE0161A312 |
| **C2002** | 1258907 | ALCA-CH 1U M 50V I G BAW SPE0161A312 |
| **C2003** | 1119192 | CECA-CH 33N K X7R 0805 BAW SPE0015A315 |
| **C2004** | 1296116 | CECA-CH 3N9 K X7R 0603 50V BAW SPE0032A3 |
| **C2005** | 1296116 | CECA-CH 3N9 K X7R 0603 50V BAW SPE0032A3 |
| **C2006** | 1119176 | CECA-CH 22N J X7R 0805 BAW SPE0014A315 |
| **C2007** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C2008** | 1255711 | CECA-CH 220N J X7R 1206 BAW SPE0037A315 |
| **C2009** | 1255711 | CECA-CH 220N J X7R 1206 BAW SPE0037A315 |
| **C201** | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| **C2010** | 1307797 | ALCA-CH 4U7 M 25V I G BAW SPE0164A312 |
| **C2011** | 1307797 | ALCA-CH 4U7 M 25V I G BAW SPE0164A312 |
| **C2012** | 1083945 | CECA-CH 2N7 J NP0 1206 BAW SPE0007A315 |
| **C2013** | 1307797 | ALCA-CH 4U7 M 25V I G BAW SPE0164A312 |
| **C2014** | 1182943 | CECA-CH 47N K X7R 0805 BAW SPE0015A315 |

| | | |
|---|---|---|
| **C2015** | 1182943 | CECA-CH 47N K X7R 0805 BAW SPE0015A315 |
| **C2016** | 1275879 | ALCA-CH 10U M 16V I G BAW SPE0162A312 |
| **C2017** | 1307797 | ALCA-CH 4U7 M 25V I G BAW SPE0164A312 |
| **C2018** | 1083945 | CECA-CH 2N7 J NP0 1206 BAW SPE0007A315 |
| **C2019** | 1223976 | CECA-CH 47P J NP0 0603 BAW SPE0030A315 |
| **C202** | 1182943 | CECA-CH 47N K X7R 0805 BAW SPE0015A315 |
| **C2020** | 1258907 | ALCA-CH 1U M 50V I G BAW SPE0161A312 |
| **C2021** | 1255711 | CECA-CH 220N J X7R 1206 BAW SPE0037A315 |
| **C2022** | 1288962 | CECA-CH 150N K X7R 0805 25V MUR GRM40 |
| **C2023** | 1255711 | CECA-CH 220N J X7R 1206 BAW SPE0037A315 |
| **C2024** | 1288962 | CECA-CH 150N K X7R 0805 25V MUR GRM40 |
| **C2025** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C203** | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| **C204** | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| **C205** | 1182943 | CECA-CH 47N K X7R 0805 BAW SPE0015A315 |
| **C206** | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| **C207** | 1182943 | CECA-CH 47N K X7R 0805 BAW SPE0015A315 |
| **C209** | 1234536 | CECA-CH 100P J NP0 0603 BAW SPE0030A315 |
| **C210** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C212** | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| **C213** | 1119192 | CECA-CH 33N K X7R 0805 BAW SPE0015A315 |
| **C216** | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| **C217** | 1290681 | CECA-CH 330P J P2H 0805 50V MUR GRM40 |
| **C218** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C219** | 1283235 | CECA-CH 4U7 K X5R 1206 10V MUR GMR42-6 |
| **C220** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C221** | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| **C226** | 1275992 | CECA-CH 330P J NP0 0603 BAW SPE0030A315 |
| **C227** | 1182943 | CECA-CH 47N K X7R 0805 BAW SPE0015A315 |
| **C251** | 1320513 | CECA-CH 75P J NPO 0603 BAW SPE0030A315 |
| **C252** | 1283499 | CECA-CH 1U K X7R 0805 10V MUR GRM 40 |
| **C253** | 1223951 | CECA-CH 22P J NP0 0603 BAW SPE0030A315 |
| **C254** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C255** | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| **C257** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C258** | 1283499 | CECA-CH 1U K X7R 0805 10V MUR GRM 40 |
| **C259** | 1166409 | CECA-CH 6N8 J X7R 0805 BAW SPE0014A315 |
| **C260** | 1166409 | CECA-CH 6N8 J X7R 0805 BAW SPE0014A315 |
| **C261** | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| **C264** | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| **C271** | 1277790 | CECA-CH 680P J COH 0603 25V G MUR GRM39 |
| **C276** | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| **C277** | 1182943 | CECA-CH 47N K X7R 0805 BAW SPE0015A315 |
| **C278** | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| **C279** | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| **C282** | 1301497 | CECA-CH 47P J P2H 0603 MUR GRM39 |
| **C283** | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |

| | | |
|---|---|---|
| **C285** | 1243934 | AL-ELCA 10U M 16V G BAW SPE0069A31 RM2,5 |
| **C301** | 1230077 | CECA-CH 1N J NPO 0603 50V AVX CM105 |
| **C302** | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| **C303** | 1246321 | CECA-CH 220N K X7R 1206 BAW SPE0036A315 |
| **C304** | 1246321 | CECA-CH 220N K X7R 1206 BAW SPE0036A315 |
| **C305** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C309** | 1233971 | CECA-CH 10P J NP0 0603 BAW SPE0030A315 |
| **C310** | 1243012 | CECA-CH 27P J NPO 0603 BAW SPE0030A315 |
| **C312** | 1223933 | CECA-CH 15P J NP0 0603 BAW SPE0030A315 |
| **C314** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C317** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C318** | 1283235 | CECA-CH 4U7 K X5R 1206 10V MUR GMR42-6 |
| **C319** | 1283235 | CECA-CH 4U7 K X5R 1206 10V MUR GMR42-6 |
| **C320** | 1119060 | CECA-CH 1N K X7R 0805 BAW SPE0015A315 |
| **C321** | 1182943 | CECA-CH 47N K X7R 0805 BAW SPE0015A315 |
| **C322** | 1182943 | CECA-CH 47N K X7R 0805 BAW SPE0015A315 |
| **C323** | 1173278 | AL-ELCA 4U7 M 25V G BAW SPE0071A31 RM2,5 |
| **C324** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C325** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C326** | 1218506 | CECA-CH 1N J U2J 0805 MUR GRM40 |
| **C328** | 1259253 | CECA-CH 220P J NPO 0603 BAW SPE0030A315 |
| **C346** | 1162241 | CECA-CH 470P G NP0 0805 BAW SPE0027A315 |
| **C347** | 1162284 | CECA-CH 560P G NP0 0805 BAW SPE0027A315 |
| **C348** | 1254782 | CECA-CH 2N G NPO 0805 50V MUR GRM40 |
| **C349** | 1239961 | CECA-CH 1N F NP0 0805 BAW SPE0029A315 |
| **C351** | 1243934 | AL-ELCA 10U M 16V G BAW SPE0069A31 RM2,5 |
| **C360** | 1283235 | CECA-CH 4U7 K X5R 1206 10V MUR GMR42-6 |
| **C361** | 1119192 | CECA-CH 33N K X7R 0805 BAW SPE0015A315 |
| **C362** | 1283499 | CECA-CH 1U K X7R 0805 10V MUR GRM 40 |
| **C363** | 1270648 | CECA-CH 68N J X7R 0805 25V MUR GRM40 |
| **C364** | 1119192 | CECA-CH 33N K X7R 0805 BAW SPE0015A315 |
| **C365** | 1119192 | CECA-CH 33N K X7R 0805 BAW SPE0015A315 |
| **C366** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C367** | 1119192 | CECA-CH 33N K X7R 0805 BAW SPE0015A315 |
| **C368** | 1276220 | CECA-CH 2N2 J X7R 0805 50V BAW SPE0014A |
| **C369** | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| **C370** | 1246321 | CECA-CH 220N K X7R 1206 BAW SPE0036A315 |
| **C371** | 1119060 | CECA-CH 1N K X7R 0805 BAW SPE0015A315 |
| **C50** | 1229974 | AL-ELCA 100U M 25V I G BAW SPE0108 RM2,5 |
| **C501** | 1186973 | AL-ELCA 1M M 25V G BAW SPE0074A312-RM5 |
| **C502** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C506** | 1281641 | FOCA 470N J 50V G BAW SPE0018A314 RM5 |
| **C507** | 1281641 | FOCA 470N J 50V G BAW SPE0018A314 RM5 |
| **C508** | 1281641 | FOCA 470N J 50V G BAW SPE0018A314 RM5 |
| **C509** | 1281641 | FOCA 470N J 50V G BAW SPE0018A314 RM5 |
| **C51** | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| **C52** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |

| | | |
|---|---|---|
| **C53** | 1290282 | AL-ELCA 2M2 M 25V G BAW SPE0084A312RM7,5 |
| **C54** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C55** | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| **C56** | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| **C57** | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| **C58** | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| **C59** | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| **C603** | 1182943 | CECA-CH 47N K X7R 0805 BAW SPE0015A315 |
| **C606** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C607** | 1253360 | AL-ELCA 56U M 2000/105 16V NCC SXE-VB F0 |
| **C609** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C610** | 1253360 | AL-ELCA 56U M 2000/105 16V NCC SXE-VB F0 |
| **C611** | 1234536 | CECA-CH 100P J NP0 0603 BAW SPE0030A315 |
| **C612** | 1249150 | AL-ELCA 22U M 16V BAW SPE0067A312-RM2,5 |
| **C613** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C62** | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| **C63** | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| **C64** | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| **C65** | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| **C70** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C702** | 1281437 | FOCA 100N J 63V G BAW SPE0015A314 RM5 |
| **C704** | 1307797 | ALCA-CH 4U7 M 25V I G BAW SPE0164A312 |
| **C705** | 1281283 | FOCA 15N J 63V G BAW SPE0010A314 RM5 |
| **C706** | 1275992 | CECA-CH 330P J NP0 0603 BAW SPE0030A315 |
| **C707** | 1275992 | CECA-CH 330P J NP0 0603 BAW SPE0030A315 |
| **C71** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C712** | 1281437 | FOCA 100N J 63V G BAW SPE0015A314 RM5 |
| **C714** | 1307797 | ALCA-CH 4U7 M 25V I G BAW SPE0164A312 |
| **C715** | 1281283 | FOCA 15N J 63V G BAW SPE0010A314 RM5 |
| **C716** | 1275992 | CECA-CH 330P J NP0 0603 BAW SPE0030A315 |
| **C717** | 1275992 | CECA-CH 330P J NP0 0603 BAW SPE0030A315 |
| **C72** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C720** | 1249150 | AL-ELCA 22U M 16V BAW SPE0067A312-RM2,5 |
| **C721** | 1252585 | CECA-CH 470N J X5R 1206 16V MUR GRM42-6 |
| **C722** | 1166751 | CECA-CH 4N7 K X7R 0805 BAW SPE0015A315 |
| **C723** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C724** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C725** | 1172085 | AL-ELCA 100U M 16V G BAW SPE0063A3 RM2,5 |
| **C73** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C74** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C75** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C76** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C77** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C805** | 1119060 | CECA-CH 1N K X7R 0805 BAW SPE0015A315 |
| **C806** | 1234536 | CECA-CH 100P J NP0 0603 BAW SPE0030A315 |
| **C807** | 1234536 | CECA-CH 100P J NP0 0603 BAW SPE0030A315 |
| **C808** | 1234536 | CECA-CH 100P J NP0 0603 BAW SPE0030A315 |

| | | |
|---|---|---|
| **C811** | 1234536 | CECA-CH 100P J NP0 0603 BAW SPE0030A315 |
| **C812** | 1234536 | CECA-CH 100P J NP0 0603 BAW SPE0030A315 |
| **C813** | 1234536 | CECA-CH 100P J NP0 0603 BAW SPE0030A315 |
| **C814** | 1234536 | CECA-CH 100P J NP0 0603 BAW SPE0030A315 |
| **C815** | 1234536 | CECA-CH 100P J NP0 0603 BAW SPE0030A315 |
| **C816** | 1234536 | CECA-CH 100P J NP0 0603 BAW SPE0030A315 |
| **C817** | 1234536 | CECA-CH 100P J NP0 0603 BAW SPE0030A315 |
| **C818** | 1234536 | CECA-CH 100P J NP0 0603 BAW SPE0030A315 |
| **C819** | 1234536 | CECA-CH 100P J NP0 0603 BAW SPE0030A315 |
| **C820** | 1234536 | CECA-CH 100P J NP0 0603 BAW SPE0030A315 |
| **C821** | 1229974 | AL-ELCA 100U M 25V I G BAW SPE0108 RM2,5 |
| **C830** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C831** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C832** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C833** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C834** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C835** | 1182943 | CECA-CH 47N K X7R 0805 BAW SPE0015A315 |
| **C836** | 1119117 | CECA-CH 10N J X7R 0805 BAW SPE0014A315 |
| **C837** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C840** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C852** | 1119125 | CECA-CH 10N K X7R 0805 BAW SPE0015A315 |
| **C861** | 1258907 | ALCA-CH 1U M 50V I G BAW SPE0161A312 |
| **C862** | 1258877 | AL-ELCA 4U7 M 50V G BAW SPE0049A31 RM2,5 |
| **C863** | 1258907 | ALCA-CH 1U M 50V I G BAW SPE0161A312 |
| **C870** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C871** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C881** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C882** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C897** | 1258907 | ALCA-CH 1U M 50V I G BAW SPE0161A312 |
| **C898** | 1258907 | ALCA-CH 1U M 50V I G BAW SPE0161A312 |
| **C901** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C902** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C908** | 1223951 | CECA-CH 22P J NP0 0603 BAW SPE0030A315 |
| **C909** | 1223951 | CECA-CH 22P J NP0 0603 BAW SPE0030A315 |
| **C919** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C928** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C929** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C939** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C949** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C958** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C968** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **C969** | 1246348 | CECA-CH 100N K X7R 0805 BAW SPE0035A315 |
| **D101** | 1149326 | CHOKE-CH 0,68UH K G SIE B82422-A3681-K |
| **D103** | 1289950 | CHOKE-CH 10UH K G SIE B82432-A1103-K |
| **D104** | 1242164 | INDUCTOR-CH G MUR BLM11B141D |
| **D1500** | 1237705 | INDUCTOR-CH G MUR BLM21A601S |
| **D1501** | 1305591 | INDUCTOR-CH G MUR BLM11A601S |

| | | |
|---|---|---|
| **D1502** | 1237705 | INDUCTOR-CH G MUR BLM21A601S |
| **D1503** | 1227221 | INDUCTOR-CH G MUR BLM11A221S |
| **D1504** | 1000950 | CHOKE-CH 47UH K G SIE B82422-A1473-K |
| **D1505** | 1305591 | INDUCTOR-CH G MUR BLM11A601S |
| **D1550** | 1237705 | INDUCTOR-CH G MUR BLM21A601S |
| **D1801** | 1227221 | INDUCTOR-CH G MUR BLM11A221S |
| **D301** | 1178237 | CHOKE-CH 2,2UH K G SIE B82422-A1222-K |
| **D302** | 1249398 | CHOKE-CH 2,2MH K G MSI C6-R/3333 |
| **D304** | 1245368 | CHOKE-CH 68UH K G SIE B82432-S1683-K |
| **D305** | 1245368 | CHOKE-CH 68UH K G SIE B82432-S1683-K |
| **D306** | 1148494 | CHOKE-CH 0,47UH J G SIE B82422-A3471-J |
| **D50** | 1237705 | INDUCTOR-CH G MUR BLM21A601S |
| **D51** | 1237705 | INDUCTOR-CH G MUR BLM21A601S |
| **D52** | 1237705 | INDUCTOR-CH G MUR BLM21A601S |
| **D53** | 1244922 | CHOKE,BATT.- 200UH VOG 5730409900 |
| **D870** | 1227221 | INDUCTOR-CH G MUR BLM11A221S |
| **D871** | 1227221 | INDUCTOR-CH G MUR BLM11A221S |
| **D873** | 1245104 | CHOKE-CH 51UH N 0,5A G SIE B82790 |
| **D909** | 1237705 | INDUCTOR-CH G MUR BLM21A601S |
| **D930** | 1237705 | INDUCTOR-CH G MUR BLM21A601S |
| **D931** | 1237705 | INDUCTOR-CH G MUR BLM21A601S |
| **DI101** | 1217186 | DIODE-CH SIE BB914 G |
| **DI102** | 1217186 | DIODE-CH SIE BB914 G |
| **DI104** | 1225529 | DIODE-CH TEL S391D G |
| **DI131** | 1217186 | DIODE-CH SIE BB914 G |
| **DI1801** | 1252143 | DIODE-CH PHI BAS216 G |
| **DI1803** | 1252143 | DIODE-CH PHI BAS216 G |
| **DI1804** | 1252143 | DIODE-CH PHI BAS216 G |
| **DI1805** | 1252143 | DIODE-CH PHI BAS216 G |
| **DI203** | 1252143 | DIODE-CH PHI BAS216 G |
| **DI301** | 1229788 | DIODE-CH BAW BA779-2/1SV234/DPA05 G SPE |
| **DI302** | 1252143 | DIODE-CH PHI BAS216 G |
| **DI50** | 1179683 | DIODE-CH GIC S3B G |
| **DI501** | 1252143 | DIODE-CH PHI BAS216 G |
| **DI603** | 1118757 | DIODE-CH BAW 6V8 5% SHIP-TO-STOCK G SPE0 |
| **DI830** | 1043587 | DIODE-CH BAW BAW56 SHIP-TO ST.G SPE0028A |
| **DI831** | 1043587 | DIODE-CH BAW BAW56 SHIP-TO ST.G SPE0028A |
| **DI832** | 1043587 | DIODE-CH BAW BAW56 SHIP-TO ST.G SPE0028A |
| **DI833** | 1252143 | DIODE-CH PHI BAS216 G |
| **DI834** | 1252143 | DIODE-CH PHI BAS216 G |
| **DI840** | 1076353 | DIODE-CH BAW 5V6 2% SHIP-TO-STOCK G SPE0 |
| **DI853** | 1252143 | DIODE-CH PHI BAS216 G |
| **DI854** | 1252143 | DIODE-CH PHI BAS216 G |
| **DI861** | 1043587 | DIODE-CH BAW BAW56 SHIP-TO ST.G SPE0028A |
| **DI885** | 1252143 | DIODE-CH PHI BAS216 G |
| **DI890** | 1252143 | DIODE-CH PHI BAS216 G |
| **F101** | 1295004 | FILTER, FMZ- 100MHZ TOK MC122 E528ENAS-1 |

| | | |
|---|---|---|
| **F102** | 1253395 | FILTER, FMZ- 100MHZ TOK/P666SNS-256Z-RT |
| **F131** | 1284827 | FILTER,AMO/FMO-120MHZ TOK VAG,VWA,GEA |
| **F201** | 1290568 | FILTER, FM-ZF- 10,7MHZ TOK 5PAG-C805PN- |
| **F204** | 1291637 | FILTER,FM-PHASENKR.-10,7MHZ MSI RA7008-2 |
| **F321** | 1247115 | FILTER, AM-ZF- 450KHZ TOK 5PAG (C805LN-0 |
| **IC101** | 1309404 | IC-CH SIE TUA 4306 B3 MQFP64/1 G |
| **IC1401** | 1155431 | IC-CH PHI SAA6579T/V1 SHIP-TO-STOCK |
| **IC1500** | 1239147 | IC-CH AUM OCC8001-01 |
| **IC1501** | 1249101 | IC-CH TOS TC7S08F G |
| **IC1502** | 1311050 | IC-CH AKM AK4520B-E2 |
| **IC151** | 1283510 | IC-CH SGT TDA 7427 AD (TSSOP28) G |
| **IC1801** | 0901806 | IC-CH PHI PCF8576T/F2 SHIP-TO-STOCK G |
| **IC1802** | 1299662 | IC-CH NEC UPD 754302-3200-04/98 |
| **IC2001** | 1246178 | IC-CH SGT TDA7342TR G |
| **IC361** | 1283669 | IC-CH HIT HA12181FP FP-16DA |
| **IC501** | 1271180 | IC PHI TDA8569Q /N1 |
| **IC601** | 1258397 | IC-CH SIE TLE4276GV P-TO220-5-122 |
| **IC602** | 1246674 | IC-CH SIE TLE4269GL P-DSO20-6 G |
| **IC701** | 1246607 | IC-CH SOY CXA2510Q |
| **IC702** | 1245996 | IC-CH PHI 74HC03D,653 G |
| **IC831** | 1286242 | IC-CH TOS TC7S14F G |
| **IC870** | 1279432 | IC-CH PHI TJA 1053 G |
| **IC881** | 1240481 | IC-CH SIE BSP452 G |
| **IC901** | 1245058 | IC-CH SIE SAF-C515C-8R P-MQFP-80 |
| **IC902** | 1294490 | IC-CH PHI 74HC573 PW,118-TSSOP20 |
| **IC903** | 1312170 | IC-SOCKET+C450 32POL CAB 540-99-032-07-400-0 |
| **IC903** | 1338196 | IC-CH BAW 27C010-90-3100-26/99 3100 |
| **IC904** | 1294334 | IC-CH SAY LC35256DT-70-TLM |
| **IC905** | 1294490 | IC-CH PHI 74HC573 PW,118-TSSOP20 |
| **IC906** | 1294490 | IC-CH PHI 74HC573 PW,118-TSSOP20 |
| **IC909** | 1294601 | IC-CH PHI 74HC02PW-TSSOP14 G |
| **IC910** | 1012071 | IC-CH BAW 74HC4094 G SPE0005A308 |
| **IC911** | 1012071 | IC-CH BAW 74HC4094 G SPE0005A308 |
| **KF201** | 1306987 | K-FILT MUR SFE 10,7 MS3A10GJ24-A-S-TF21 |
| **KF202** | 1331590 | KERA-FILTER MUR SFE 10,7MHZ MTE-TF22 |
| **KF204** | 1307010 | K-FILT.MUR SFE 10,7MHZ MJA10J24-A-S-TF21 |
| **KF205** | 1306987 | K-FILT MUR SFE 10,7 MS3A10GJ24-A-S-TF21 |
| **KF321** | 1237713 | KERA-FILTER MUR CFWS 450 IT |
| **LD1801** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1802** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1803** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1804** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1805** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1806** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1807** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1808** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1809** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |

| | | |
|---|---|---|
| **LD1810** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1811** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1812** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1813** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1814** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1831** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1832** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1833** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1834** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1835** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1836** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1837** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1838** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1839** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1840** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1841** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1842** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1843** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1844** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1846** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1847** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1848** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1849** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1850** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1851** | 1285122 | LED-CH SIE LYT670E9349 K2/U Q62703-Q4228 |
| **LD1861** | 1158767 | LED-CH SIE LST670 G -RT |
| **OT1500** | 1248121 | TRANSCEIVER AMP 966893 D2BOPTICAL-HEADER |
| **P701** | 1246615 | TRIRES-CH 10K 0,10W MUR POZ3AN1-103N-T00 |
| **P702** | 1246615 | TRIRES-CH 10K 0,10W MUR POZ3AN1-103N-T00 |
| **Q1401** | 1277898 | QUARTZ 4,332MHZ G NDK AT-51 |
| **Q1500** | 1305492 | QUARTZ-CH 16,9344 MHZ NDK AT-41CD2 |
| **Q151** | 1280279 | QUARTZ 10,250 MHZ G NDK AT-51 M.ISOPL. |
| **Q1801** | 1171501 | KERA-RESON-CH MUR CSAC 4,19 MGCA G |
| **Q251** | 1295268 | KERA-RESON-CH MUR CSBF456 JF 239 |
| **Q901** | 1295691 | QUARTZ 10MHZ TQG TQX6674 MIT ISOPL. |
| **R1000** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **R1002** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **R1004** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **R1005** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R1006** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R1007** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R1008** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R1009** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R1010** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R1011** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R1012** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R102** | 1304445 | RES-CH 1K F 0603 BAW SPE0028A323 |

| | | |
|---|---|---|
| **R103** | 1304161 | RES-CH 10R F 0603 BAW SPE0027A323 |
| **R105** | 1304161 | RES-CH 10R F 0603 BAW SPE0027A323 |
| **R106** | 1271199 | RES-CH 56K F 0603 G BAW SPE0028A323 |
| **R107** | 1304161 | RES-CH 10R F 0603 BAW SPE0027A323 |
| **R112** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **R1160** | 1305085 | RES-CH 820K F 0603 BAW SPE0028A323 |
| **R1161** | 1304445 | RES-CH 1K F 0603 BAW SPE0028A323 |
| **R121** | 1297041 | RES-CH 10K F 0603 G BAW SPE0028A323 |
| **R122** | 1271199 | RES-CH 56K F 0603 G BAW SPE0028A323 |
| **R123** | 1297041 | RES-CH 10K F 0603 G BAW SPE0028A323 |
| **R124** | 1271199 | RES-CH 56K F 0603 G BAW SPE0028A323 |
| **R125** | 1297041 | RES-CH 10K F 0603 G BAW SPE0028A323 |
| **R126** | 1285564 | RES-CH 4K7 F 0603 G BAW SPE0028A323 |
| **R127** | 1304445 | RES-CH 1K F 0603 BAW SPE0028A323 |
| **R131** | 1297041 | RES-CH 10K F 0603 G BAW SPE0028A323 |
| **R132** | 1297041 | RES-CH 10K F 0603 G BAW SPE0028A323 |
| **R1401** | 1304161 | RES-CH 10R F 0603 BAW SPE0027A323 |
| **R1402** | 1304437 | RES-CH 820R F 0603 BAW SPE0027A323 |
| **R1500** | 1304471 | RES-CH 2K F 0603 G BAW SPE0028A323 |
| **R1501** | 1271202 | RES-CH 220K F 0603 G BAW SPE0028A323 |
| **R1502** | 1277588 | RES-CH 330K F 0603 G BAW SPE 0028A323 |
| **R1503** | 1304755 | RES-CH 1R5 F 0805 G BAW SPE0017A323 |
| **R1506** | 1304364 | RES-CH 270R F 0603 BAW SPE0027A323 |
| **R1507** | 1304364 | RES-CH 270R F 0603 BAW SPE0027A323 |
| **R1508** | 1304364 | RES-CH 270R F 0603 BAW SPE0027A323 |
| **R1509** | 1304364 | RES-CH 270R F 0603 BAW SPE0027A323 |
| **R151** | 1297041 | RES-CH 10K F 0603 G BAW SPE0028A323 |
| **R1511** | 1304410 | RES-CH 560R F 0603 BAW SPE0027A323 |
| **R1512** | 1304410 | RES-CH 560R F 0603 BAW SPE0027A323 |
| **R1513** | 1304410 | RES-CH 560R F 0603 BAW SPE0027A323 |
| **R1514** | 1304410 | RES-CH 560R F 0603 BAW SPE0027A323 |
| **R1515** | 1304410 | RES-CH 560R F 0603 BAW SPE0027A323 |
| **R1516** | 1304410 | RES-CH 560R F 0603 BAW SPE0027A323 |
| **R1517** | 1271199 | RES-CH 56K F 0603 G BAW SPE0028A323 |
| **R1518** | 1235389 | RES-CH 2K4 F 0603 G BAW SPE0028A323 |
| **R1519** | 1235389 | RES-CH 2K4 F 0603 G BAW SPE0028A323 |
| **R152** | 1304161 | RES-CH 10R F 0603 BAW SPE0027A323 |
| **R1520** | 1271199 | RES-CH 56K F 0603 G BAW SPE0028A323 |
| **R1521** | 1304321 | RES-CH 150R F 0603 BAW SPE0027A323 |
| **R1522** | 1304321 | RES-CH 150R F 0603 BAW SPE0027A323 |
| **R1523** | 1304364 | RES-CH 270R F 0603 BAW SPE0027A323 |
| **R1524** | 1304364 | RES-CH 270R F 0603 BAW SPE0027A323 |
| **R1525** | 1304364 | RES-CH 270R F 0603 BAW SPE0027A323 |
| **R1526** | 1304364 | RES-CH 270R F 0603 BAW SPE0027A323 |
| **R1527** | 1304364 | RES-CH 270R F 0603 BAW SPE0027A323 |
| **R1528** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R153** | 1253700 | RES-CH 8K2 F 0603 G BAW SPE0028A323 |

| | | |
|---|---|---|
| **R154** | 1304445 | RES-CH 1K F 0603 BAW SPE0028A323 |
| **R1550** | 1304445 | RES-CH 1K F 0603 BAW SPE0028A323 |
| **R1551** | 1304410 | RES-CH 560R F 0603 BAW SPE0027A323 |
| **R156** | 1305001 | RES-CH 33K F 0603 BAW SPE0028A323 |
| **R157** | 1304161 | RES-CH 10R F 0603 BAW SPE0027A323 |
| **R159** | 1304445 | RES-CH 1K F 0603 BAW SPE0028A323 |
| **R161** | 1304445 | RES-CH 1K F 0603 BAW SPE0028A323 |
| **R163** | 1227661 | RES-CH 0R 0603 BAW SPE0025A323 |
| **R165** | 1297041 | RES-CH 10K F 0603 G BAW SPE0028A323 |
| **R166** | 1297041 | RES-CH 10K F 0603 G BAW SPE0028A323 |
| **R168** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R169** | 1304161 | RES-CH 10R F 0603 BAW SPE0027A323 |
| **R1801** | 1226649 | RES-CH 680R F 1206 BAW SPE0015A323 |
| **R1802** | 1293206 | RES-CH 1K5 F 1206 BAW SPE0016A323 |
| **R1803** | 1293206 | RES-CH 1K5 F 1206 BAW SPE0016A323 |
| **R1804** | 1293206 | RES-CH 1K5 F 1206 BAW SPE0016A323 |
| **R1805** | 1293206 | RES-CH 1K5 F 1206 BAW SPE0016A323 |
| **R1809** | 1303511 | RES-CH 560R F 1206 G BAW SPE0015A323 |
| **R1810** | 1303511 | RES-CH 560R F 1206 G BAW SPE0015A323 |
| **R1811** | 1303511 | RES-CH 560R F 1206 G BAW SPE0015A323 |
| **R1812** | 1303511 | RES-CH 560R F 1206 G BAW SPE0015A323 |
| **R1813** | 1303538 | RES-CH 820R F 1206 G BAW SPE0015A323 |
| **R1814** | 1303491 | RES-CH 470R F 1206 G BAW SPE0015A323 |
| **R1815** | 1226649 | RES-CH 680R F 1206 BAW SPE0015A323 |
| **R1816** | 1304437 | RES-CH 820R F 0603 BAW SPE0027A323 |
| **R1817** | 1304437 | RES-CH 820R F 0603 BAW SPE0027A323 |
| **R1818** | 1304437 | RES-CH 820R F 0603 BAW SPE0027A323 |
| **R1819** | 1304437 | RES-CH 820R F 0603 BAW SPE0027A323 |
| **R1831** | 1304445 | RES-CH 1K F 0603 BAW SPE0028A323 |
| **R1832** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R1833** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R1836** | 1305158 | RES-CH 100K F 0603 BAW SPE0028A323 |
| **R1837** | 1305093 | RES-CH 1M F 0603 BAW SPE0028A323 |
| **R1841** | 1304402 | RES-CH 470R F 0603 BAW SPE0027A323 |
| **R1842** | 1285564 | RES-CH 4K7 F 0603 G BAW SPE0028A323 |
| **R1844** | 1305158 | RES-CH 100K F 0603 BAW SPE0028A323 |
| **R1846** | 1305158 | RES-CH 100K F 0603 BAW SPE0028A323 |
| **R1847** | 1305158 | RES-CH 100K F 0603 BAW SPE0028A323 |
| **R1848** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R1849** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R1851** | 1304331 | RES-CH 180R F 0603 BAW SPE0027A323 |
| **R1852** | 1304305 | RES-CH 120R F 0603 G BAW SPE0027A323 |
| **R1854** | 1304402 | RES-CH 470R F 0603 BAW SPE0027A323 |
| **R1861** | 1282662 | RES-CH 180K F 0603 G BAW SPE0028A323 |
| **R1862** | 1288415 | RES-CH 6K8 F 0603 G BAW SPE 0028A323 |
| **R1864** | 1288393 | RES-CH 5K1 F 0603 G BAW SPE0028A323 |
| **R1865** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |

| | | |
|---|---|---|
| **R2001** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R2002** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **R2003** | 1254022 | RES-CH 2K2 F 0603 G BAW SPE0028A323 |
| **R2004** | 1304496 | RES-CH 3K9 F 0603 G BAW SPE0028A323 |
| **R2005** | 1304496 | RES-CH 3K9 F 0603 G BAW SPE0028A323 |
| **R2006** | 1304496 | RES-CH 3K9 F 0603 G BAW SPE0028A323 |
| **R2007** | 1304496 | RES-CH 3K9 F 0603 G BAW SPE0028A323 |
| **R2008** | 1253700 | RES-CH 8K2 F 0603 G BAW SPE0028A323 |
| **R2009** | 1227661 | RES-CH 0R 0603 BAW SPE0025A323 |
| **R201** | 1304364 | RES-CH 270R F 0603 BAW SPE0027A323 |
| **R2010** | 1253700 | RES-CH 8K2 F 0603 G BAW SPE0028A323 |
| **R2011** | 1227661 | RES-CH 0R 0603 BAW SPE0025A323 |
| **R2012** | 1291181 | RES-CH 5K6 F 0603 G BAW SPE0028A323 |
| **R2013** | 1291181 | RES-CH 5K6 F 0603 G BAW SPE0028A323 |
| **R202** | 1304445 | RES-CH 1K F 0603 BAW SPE0028A323 |
| **R203** | 1254448 | RES-CH 27K F 0603 G BAW SPE0028A323 |
| **R204** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **R205** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **R206** | 1304232 | RES-CH 47R F 0603 G BAW SPE0027A323 |
| **R207** | 1254431 | RES-CH 20K F 0603 G BAW SPE0028A323 |
| **R208** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R209** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R210** | 1304161 | RES-CH 10R F 0603 BAW SPE0027A323 |
| **R211** | 1304399 | RES-CH 390R F 0603 BAW SPE0027A323 |
| **R212** | 1304161 | RES-CH 10R F 0603 BAW SPE0027A323 |
| **R213** | 1304161 | RES-CH 10R F 0603 BAW SPE0027A323 |
| **R214** | 1246623 | RES-CH 430K F 0603 G BAW SPE0028A323 |
| **R215** | 1304496 | RES-CH 3K9 F 0603 G BAW SPE0028A323 |
| **R221** | 1258478 | RES-CH 15K F 0603 BAW SPE0028A323 |
| **R222** | 1258486 | RES-CH 39K F 0603 BAW SPE0028A323 |
| **R223** | 1257838 | NTCRES-CH 220R J 0805 SIE B57620-C221-J62 |
| **R224** | 1285564 | RES-CH 4K7 F 0603 G BAW SPE0028A323 |
| **R225** | 1304380 | RES-CH 330R F 0603 BAW SPE0027A323 |
| **R227** | 1282700 | RES-CH 120K F 0603 G BAW SPE 0028A323 |
| **R228** | 1282662 | RES-CH 180K F 0603 G BAW SPE0028A323 |
| **R229** | 1304488 | RES-CH 2K7 F 0603 BAW SPE0028A323 |
| **R230** | 1313185 | RES-CH 51K F 0603 G BAW SPE 0028 A 323 |
| **R231** | 1304445 | RES-CH 1K F 0603 BAW SPE0028A323 |
| **R232** | 1305131 | RES-CH 68K F 0603 BAW SPE0028A323 |
| **R235** | 1254340 | RES-CH 270K F 0603 G BAW SPE0028A323 |
| **R236** | 1305018 | RES-CH 150K F 0603 BAW SPE0028A323 |
| **R240** | 1304445 | RES-CH 1K F 0603 BAW SPE0028A323 |
| **R241** | 1271202 | RES-CH 220K F 0603 G BAW SPE0028A323 |
| **R242** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **R243** | 1305069 | RES-CH 560K F 0603 BAW SPE0028A323 |
| **R244** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R245** | 1304402 | RES-CH 470R F 0603 BAW SPE0027A323 |


| | | |
|---|---|---|
| **R246** | 1305131 | RES-CH 68K F 0603 BAW SPE0028A323 |
| **R247** | 1297041 | RES-CH 10K F 0603 G BAW SPE0028A323 |
| **R248** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **R249** | 1285564 | RES-CH 4K7 F 0603 G BAW SPE0028A323 |
| **R251** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **R252** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **R253** | 1305158 | RES-CH 100K F 0603 BAW SPE0028A323 |
| **R254** | 1297041 | RES-CH 10K F 0603 G BAW SPE0028A323 |
| **R255** | 1297041 | RES-CH 10K F 0603 G BAW SPE0028A323 |
| **R256** | 1227661 | RES-CH 0R 0603 BAW SPE0025A323 |
| **R257** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R269** | 1304348 | RES-CH 220R F 0603 BAW SPE0027A323 |
| **R270** | 1304313 | RES-CH 130R F 0603 G BAW SPE0027A323 |
| **R271** | 1304348 | RES-CH 220R F 0603 BAW SPE0027A323 |
| **R274** | 1277588 | RES-CH 330K F 0603 G BAW SPE 0028A323 |
| **R275** | 1302965 | RES-CH 130K F 0603 G BAW SPE0028A323 |
| **R276** | 1305158 | RES-CH 100K F 0603 BAW SPE0028A323 |
| **R277** | 1304348 | RES-CH 220R F 0603 BAW SPE0027A323 |
| **R279** | 1285564 | RES-CH 4K7 F 0603 G BAW SPE0028A323 |
| **R285** | 1304402 | RES-CH 470R F 0603 BAW SPE0027A323 |
| **R287** | 1305158 | RES-CH 100K F 0603 BAW SPE0028A323 |
| **R288** | 1305158 | RES-CH 100K F 0603 BAW SPE0028A323 |
| **R290** | 1304445 | RES-CH 1K F 0603 BAW SPE0028A323 |
| **R296** | 1227661 | RES-CH 0R 0603 BAW SPE0025A323 |
| **R297** | 1304291 | RES-CH 110R F 0603 G BAW SPE0027A323 |
| **R301** | 1305050 | RES-CH 470K F 0603 BAW SPE0028A323 |
| **R302** | 1304852 | RES-CH 47R F 0805 G BAW SPE0017A323 |
| **R306** | 1254022 | RES-CH 2K2 F 0603 G BAW SPE0028A323 |
| **R307** | 1304178 | RES-CH 18R F 0603 BAW SPE0027A323 |
| **R312** | 1304402 | RES-CH 470R F 0603 BAW SPE0027A323 |
| **R313** | 1288415 | RES-CH 6K8 F 0603 G BAW SPE 0028A323 |
| **R316** | 1304259 | RES-CH 68R F 0603 BAW SPE0027A323 |
| **R317** | 1304380 | RES-CH 330R F 0603 BAW SPE0027A323 |
| **R318** | 1305093 | RES-CH 1M F 0603 BAW SPE0028A323 |
| **R321** | 1304161 | RES-CH 10R F 0603 BAW SPE0027A323 |
| **R323** | 1304399 | RES-CH 390R F 0603 BAW SPE0027A323 |
| **R324** | 1304380 | RES-CH 330R F 0603 BAW SPE0027A323 |
| **R327** | 1258478 | RES-CH 15K F 0603 BAW SPE0028A323 |
| **R328** | 1304461 | RES-CH 1K5 F 0603 G BAW SPE0028A323 |
| **R329** | 1285564 | RES-CH 4K7 F 0603 G BAW SPE0028A323 |
| **R331** | 1281811 | RES-CH 1K8 F 0603 G BAW SPE0028A323 |
| **R347** | 1305131 | RES-CH 68K F 0603 BAW SPE0028A323 |
| **R348** | 1282700 | RES-CH 120K F 0603 G BAW SPE 0028A323 |
| **R349** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **R350** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **R351** | 1254340 | RES-CH 270K F 0603 G BAW SPE0028A323 |
| **R352** | 1254324 | RES-CH 24K F 0603 G BAW SPE0028A323 |

| | | |
|---|---|---|
| **R353** | 1304445 | RES-CH 1K F 0603 BAW SPE0028A323 |
| **R360** | 1305158 | RES-CH 100K F 0603 BAW SPE0028A323 |
| **R361** | 1254421 | RES-CH 12K F 0603 G BAW SPE0028A323 |
| **R362** | 1285564 | RES-CH 4K7 F 0603 G BAW SPE0028A323 |
| **R363** | 1282662 | RES-CH 180K F 0603 G BAW SPE0028A323 |
| **R364** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R365** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **R370** | 1018302 | RES-CH 0R 0805 G BAW SPE0009A323 |
| **R50** | 1303112 | RES-CH 15R F 1206 G BAW SPE0015A323 |
| **R501** | 1297041 | RES-CH 10K F 0603 G BAW SPE0028A323 |
| **R506** | 1281811 | RES-CH 1K8 F 0603 G BAW SPE0028A323 |
| **R507** | 1281811 | RES-CH 1K8 F 0603 G BAW SPE0028A323 |
| **R508** | 1281811 | RES-CH 1K8 F 0603 G BAW SPE0028A323 |
| **R509** | 1281811 | RES-CH 1K8 F 0603 G BAW SPE0028A323 |
| **R51** | 1303112 | RES-CH 15R F 1206 G BAW SPE0015A323 |
| **R52** | 1303112 | RES-CH 15R F 1206 G BAW SPE0015A323 |
| **R602** | 1159496 | RES-CH 22K F 0805 G BAW SPE0018A323 |
| **R603** | 1285564 | RES-CH 4K7 F 0603 G BAW SPE0028A323 |
| **R604** | 1258478 | RES-CH 15K F 0603 BAW SPE0028A323 |
| **R605** | 1258486 | RES-CH 39K F 0603 BAW SPE0028A323 |
| **R608** | 1304364 | RES-CH 270R F 0603 BAW SPE0027A323 |
| **R609** | 1304283 | RES-CH 100R F 0603 BAW SPE0027A323 |
| **R614** | 1304445 | RES-CH 1K F 0603 BAW SPE0028A323 |
| **R615** | 1304445 | RES-CH 1K F 0603 BAW SPE0028A323 |
| **R618** | 1297041 | RES-CH 10K F 0603 G BAW SPE0028A323 |
| **R619** | 1297041 | RES-CH 10K F 0603 G BAW SPE0028A323 |
| **R620** | 1297041 | RES-CH 10K F 0603 G BAW SPE0028A323 |
| **R621** | 1297041 | RES-CH 10K F 0603 G BAW SPE0028A323 |
| **R623** | 1227661 | RES-CH 0R  0603 BAW SPE0025A323 |
| **R701** | 1304526 | RES-CH 11K F 0603 G TK100 BAW SPE0028A |
| **R702** | 1304518 | RES-CH 16K F 0603 G BAW SPE0028A323 |
| **R703** | 1282662 | RES-CH 180K F 0603 G BAW SPE0028A323 |
| **R704** | 1304283 | RES-CH 100R F 0603 BAW SPE0027A323 |
| **R711** | 1304526 | RES-CH 11K F 0603 G TK100 BAW SPE0028A |
| **R712** | 1304518 | RES-CH 16K F 0603 G BAW SPE0028A323 |
| **R713** | 1282662 | RES-CH 180K F 0603 G BAW SPE0028A323 |
| **R714** | 1304283 | RES-CH 100R F 0603 BAW SPE0027A323 |
| **R720** | 1248197 | RES-CH 18K F 0603 G BAW SPE0028A323 |
| **R721** | 1304496 | RES-CH 3K9 F 0603 G BAW SPE0028A323 |
| **R722** | 1305131 | RES-CH 68K F 0603 BAW SPE0028A323 |
| **R723** | 1305050 | RES-CH 470K F 0603 BAW SPE0028A323 |
| **R725** | 1305001 | RES-CH 33K F 0603 BAW SPE0028A323 |
| **R726** | 1305001 | RES-CH 33K F 0603 BAW SPE0028A323 |
| **R727** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **R728** | 1304161 | RES-CH 10R F 0603 BAW SPE0027A323 |
| **R729** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R730** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |

| | | |
|---|---|---|
| **R732** | 1227661 | RES-CH 0R 0603 BAW SPE0025A323 |
| **R735** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **R736** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **R809** | 1297041 | RES-CH 10K F 0603 G BAW SPE0028A323 |
| **R810** | 1226657 | RES-CH 1K F 1206 BAW SPE0016A323 |
| **R811** | 1304445 | RES-CH 1K F 0603 BAW SPE0028A323 |
| **R820** | 1283367 | RES-CH 10R F 1206 G TK100 BAW0015A323 |
| **R821** | 1283367 | RES-CH 10R F 1206 G TK100 BAW0015A323 |
| **R822** | 1283367 | RES-CH 10R F 1206 G TK100 BAW0015A323 |
| **R830** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R831** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **R832** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **R833** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R834** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R835** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **R836** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **R837** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R838** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R839** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **R841** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **R842** | 1305050 | RES-CH 470K F 0603 BAW SPE0028A323 |
| **R843** | 1271199 | RES-CH 56K F 0603 G BAW SPE0028A323 |
| **R844** | 1226592 | RES-CH 100R F 1206 BAW SPE0015A323 |
| **R845** | 1304348 | RES-CH 220R F 0603 BAW SPE0027A323 |
| **R846** | 1159496 | RES-CH 22K F 0805 G BAW SPE0018A323 |
| **R847** | 1297041 | RES-CH 10K F 0603 G BAW SPE0028A323 |
| **R848** | 1305131 | RES-CH 68K F 0603 BAW SPE0028A323 |
| **R850** | 1258478 | RES-CH 15K F 0603 BAW SPE0028A323 |
| **R851** | 1304445 | RES-CH 1K F 0603 BAW SPE0028A323 |
| **R852** | 1254022 | RES-CH 2K2 F 0603 G BAW SPE0028A323 |
| **R853** | 1304429 | RES-CH 680R F 0603 BAW SPE0027A323 |
| **R854** | 1304186 | RES-CH 22R F 0603 BAW SPE0027A323 |
| **R855** | 1297041 | RES-CH 10K F 0603 G BAW SPE0028A323 |
| **R857** | 1304186 | RES-CH 22R F 0603 BAW SPE0027A323 |
| **R859** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **R860** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R861** | 1304445 | RES-CH 1K F 0603 BAW SPE0028A323 |
| **R862** | 1254421 | RES-CH 12K F 0603 G BAW SPE0028A323 |
| **R863** | 1235397 | RES-CH 3K3 F 0603 G BAW SPE0028A323 |
| **R864** | 1305158 | RES-CH 100K F 0603 BAW SPE0028A323 |
| **R865** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **R872** | 1328417 | RES-CH 1K6 F 0603 G BAW SPE0028A323 |
| **R873** | 1328417 | RES-CH 1K6 F 0603 G BAW SPE0028A323 |
| **R881** | 1297041 | RES-CH 10K F 0603 G BAW SPE0028A323 |
| **R882** | 1297041 | RES-CH 10K F 0603 G BAW SPE0028A323 |
| **R883** | 1297041 | RES-CH 10K F 0603 G BAW SPE0028A323 |
| **R885** | 1297041 | RES-CH 10K F 0603 G BAW SPE0028A323 |

| | | |
|---|---|---|
| **R886** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R887** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R888** | 1297041 | RES-CH 10K F 0603 G BAW SPE0028A323 |
| **R890** | 1297041 | RES-CH 10K F 0603 G BAW SPE0028A323 |
| **R891** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R892** | 1297058 | RES-CH 22K F 0603 G BAW SPE0028A323 |
| **R893** | 1304445 | RES-CH 1K F 0603 BAW SPE0028A323 |
| **R897** | 1297041 | RES-CH 10K F 0603 G BAW SPE0028A323 |
| **R898** | 1297041 | RES-CH 10K F 0603 G BAW SPE0028A323 |
| **R908** | 1304283 | RES-CH 100R F 0603 BAW SPE0027A323 |
| **R914** | 1304445 | RES-CH 1K F 0603 BAW SPE0028A323 |
| **R915** | 1304410 | RES-CH 560R F 0603 BAW SPE0027A323 |
| **R916** | 1304445 | RES-CH 1K F 0603 BAW SPE0028A323 |
| **R920** | 1304410 | RES-CH 560R F 0603 BAW SPE0027A323 |
| **R934** | 1304445 | RES-CH 1K F 0603 BAW SPE0028A323 |
| **R935** | 1304445 | RES-CH 1K F 0603 BAW SPE0028A323 |
| **R942** | 1304410 | RES-CH 560R F 0603 BAW SPE0027A323 |
| **R947** | 1304445 | RES-CH 1K F 0603 BAW SPE0028A323 |
| **R956** | 1304445 | RES-CH 1K F 0603 BAW SPE0028A323 |
| **R957** | 1304410 | RES-CH 560R F 0603 BAW SPE0027A323 |
| **R988** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **R989** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **R998** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **R999** | 1254332 | RES-CH 47K F 0603 G BAW SPE0028A323 |
| **RN900** | 1298720 | WID-NETZ 4X1K J ROH MNR14 E0ABJ102 |
| **RN901** | 1298720 | WID-NETZ 4X1K J ROH MNR14 E0ABJ102 |
| **RN901C** | 1298720 | WID-NETZ 4X1K J ROH MNR14 E0ABJ102 |
| **RN902** | 1298720 | WID-NETZ 4X1K J ROH MNR14 E0ABJ102 |
| **RN903** | 1298720 | WID-NETZ 4X1K J ROH MNR14 E0ABJ102 |
| **RN904** | 1298720 | WID-NETZ 4X1K J ROH MNR14 E0ABJ102 |
| **RN905** | 1298720 | WID-NETZ 4X1K J ROH MNR14 E0ABJ102 |
| **RN906** | 1298720 | WID-NETZ 4X1K J ROH MNR14 E0ABJ102 |
| **RN907** | 1298720 | WID-NETZ 4X1K J ROH MNR14 E0ABJ102 |
| **RN908** | 1298720 | WID-NETZ 4X1K J ROH MNR14 E0ABJ102 |
| **RN909** | 1298720 | WID-NETZ 4X1K J ROH MNR14 E0ABJ102 |
| **S1831** | 1319167 | ENCODER ALP EC11E 15244 |
| **SP101** | 1031112 | ARRESTER MMC DSP-201M-A21R |
| **ST701** | 1158041 | PIN LEDGE 19POL D&R 3 302 02 01 1490 |
| **ST801** | 1252641 | PRESSURE SPRING+C823 AMP 969600-1 |
| **T101** | 1258680 | TRANSISTOR-CH TEL S949TR G |
| **T1151** | 1303317 | TRANSISTOR-CH SAY 2SC2814 F4+F5 NPN G |
| **T151** | 1289772 | TRANSISTOR-CH SIE BCR 198S PNP G |
| **T1801** | 0659614 | TRANSISTOR-CH BAW BC848B G SPE0003A |
| **T1802** | 0675318 | TRANSISTOR-CH BAW BC818-16 SHIP-TO-STOCK |
| **T1803** | 1172646 | TRANSISTOR-CH BAW KRC103S/DTC124 NP |
| **T1805** | 1239066 | TRANS.-CH BAW KRC104S/BCR148/DTC144 |
| **T1806** | 1182821 | TRANSISTOR-CH BAW KRC102S/DTC114 NP |

| | | |
|---|---|---|
| **T201** | 1303317 | TRANSISTOR-CH SAY 2SC2814 F4+F5 NPN G |
| **T202** | 1303317 | TRANSISTOR-CH SAY 2SC2814 F4+F5 NPN G |
| **T203** | 1290924 | TRANSISTOR-CH SIE BC847PN G |
| **T204** | 1307541 | TRANSISTOR-CH SIE BC847S NPN G |
| **T205** | 1307541 | TRANSISTOR-CH SIE BC847S NPN G |
| **T206** | 1289799 | TRANSISTOR-CH SIE BCR 108S NPN G |
| **T211** | 1307551 | TRANSISTOR-CH SIE BC857S PNP G |
| **T301** | 1180576 | TRANSISTOR BAW J109/110 SELEKT.G SP |
| **T302** | 0659622 | TRANSISTOR-CH BAW BC848C G SPE0004A302 |
| **T304** | 1028049 | TRANSISTOR-CH BAW BC858C G SPE0002A302 |
| **T341** | 0659622 | TRANSISTOR-CH BAW BC848C G SPE0004A302 |
| **T501** | 1172654 | TRANSISTOR-CH BAW KRA103S/DTA124 PN |
| **T502** | 1172646 | TRANSISTOR-CH BAW KRC103S/DTC124 NP |
| **T601** | 1280260 | TRANSISTOR BAW 2SD2394F/2SD1913S SPE0062 |
| **T602** | 1028049 | TRANSISTOR-CH BAW BC858C G SPE0002A302 |
| **T606** | 0672521 | TRANSISTOR-CH BAW BC856B G SPE0013A |
| **T607** | 1258079 | TRANSISTOR-CH BAW BC846B G SPE0035A302 |
| **T702** | 1253611 | TRANSISTOR-CH BAW BCR158/DTA123JC SPE006 |
| **T805** | 1172654 | TRANSISTOR-CH BAW KRA103S/DTA124 PN |
| **T806** | 1182821 | TRANSISTOR-CH BAW KRC102S/DTC114 NP |
| **T807** | 1248499 | TRANSISTOR-CH BAW BCX52-16 G SPE0060A302 |
| **T808** | 1214594 | TRANSISTOR-CH BAW KRA102S/BCR183 SP |
| **T840** | 1172654 | TRANSISTOR-CH BAW KRA103S/DTA124 PN |
| **T841** | 1172646 | TRANSISTOR-CH BAW KRC103S/DTC124 NP |
| **T842** | 0659614 | TRANSISTOR-CH BAW BC848B G SPE0003A |
| **T843** | 1172646 | TRANSISTOR-CH BAW KRC103S/DTC124 NP |
| **T852** | 1172654 | TRANSISTOR-CH BAW KRA103S/DTA124 PN |
| **T853** | 1172646 | TRANSISTOR-CH BAW KRC103S/DTC124 NP |
| **T854** | 1028006 | TRANSISTOR-CH BAW BC817-40 SHIP-TO-STOCK |
| **T855** | 1172654 | TRANSISTOR-CH BAW KRA103S/DTA124 PN |
| **T861** | 1172646 | TRANSISTOR-CH BAW KRC103S/DTC124 NP |
| **T870** | 1172646 | TRANSISTOR-CH BAW KRC103S/DTC124 NP |
| **T885** | 1028049 | TRANSISTOR-CH BAW BC858C G SPE0002A302 |
| **T890** | 1028049 | TRANSISTOR-CH BAW BC858C G SPE0002A302 |


2
3
4
5
6
7
8
9
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
12 Volt
Minus an Chassis
3200/1309.765
MADE IN GERMANY
Mercedes-Benz
audio 10
SC
CC
RDS
FM
AM
CD